



Manufactured by C.E. Studio-2 s.l

Pol. Ind. La Figuera, C/ Rosa de Luxemburgo, nº34

46970 Alaquas, Valencia -SPAIN

Phone:+34 96 127 30 54

support@ramaudio.com

**Current Draw and Thermal Dissipation RAM Audio Zetta Series**

**230V AC**

Model	1/8 Power PN															
	Idle				8 ohm				4 ohm				2 ohm			
	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line
Z210	273,0	68,8	80,0	0,5	670	169	256	1,7	1396	352	534	3,5	1536	387	588	3,9
Z215	273,0	68,8	80,0	0,5	801	202	347	2,3	1388	350	602	4,0	1424	359	617	4,1
Z220	273,0	68,8	80,0	0,5	1091	275	482	3,2	1678	423	742	5,0	1678	423	742	5,0
Z236	273,0	68,8	80,0	0,5	1691	426	733	4,8	3382	852	1466	9,7	3560	897	1543	10,2
Z420	273,0	68,8	80,0	0,5	783	197	340	2,2	2792	704	1068	7,0	3072	774	1175	7,7
Z430	273,0	68,8	80,0	0,5	1602	404	694	4,6	2741	691	1188	7,8	2848	718	1235	8,1
Z440	273,0	68,8	80,0	0,5	2243	565	972	6,4	3560	897	1543	10,2	3738	942	1620	10,7
Z460	273,0	68,8	80,0	0,5	3916	987	1698	11,2	5339	1346	2315	15,2	5161	1301	2238	14,7
Z4100	273,0	68,8	80,0	0,5	2520	635	1538	10,1	5166	1302	2434	16,0	5166	1302	2434	16,0

**120V AC**

Model	1/8 Power PN															
	Idle				8 ohm				4 ohm				2 ohm			
	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line	BTU/h	kCal/h	W line	A line
Z210	523,3	131,9	153	1,0	670	169	492	3,2	1396	352	1024	6,7	1536	387	1126	7,4
Z215	523,3	131,9	153	1,0	801	202	666	4,4	1388	350	1154	7,6	1424	359	1183	7,8
Z220	523,3	131,9	153	1,0	1091	275	924	6,2	1678	423	1422	9,5	1678	423	1422	9,5
Z236	523,3	131,9	153	1,0	1691	426	1405	9,3	3382	852	2810	18,5	3560	897	2958	19,5
Z420	523,3	131,9	153	1,0	783	197	651	4,3	2792	704	2048	13,5	3072	774	2253	14,8
Z430	523,3	131,9	153	1,0	1602	404	1331	8,8	2741	691	2278	15,0	2848	718	2367	15,6
Z440	523,3	131,9	153	1,0	2243	565	1864	12,3	3560	897	2958	19,5	3738	942	3106	20,5
Z460	523,3	131,9	153	1,0	3916	987	3254	21,4	5339	1346	4438	29,2	5161	1301	4290	28,3
Z4100	523,3	131,9	153	1,0	2520	635	2948	19,4	5166	1302	4666	30,7	5166	1302	4666	30,7